



# Qwik-Switch Scene TX(5 Scene, 1 Off) Installation

## Button Linking:

**1** Connect the receiver to the lights

**2** Hold the LINK button until the LED starts flashing

**3** Then press the Scene button within 25 sec

A Receiver can link up to 30 different buttons.  
 To unlink a button: Repeat steps 2&3.  
 To clear all links in a Receiver:  
 Hold the Receiver Link Button until the LED is ON solid (10 sec) then release.

## Scene Saving:


**1** Link the OFF button to each light, one at a time. This will switch off all selected lights.

**2** Link the scene button to all the lights in the scene. Link one light at a time.

**3** Set the light levels for the Scene, using a standard transmitter, or the test button on the side of the receiver.

**4** Hold the Scene button for 15 seconds to save...Done

## Scene Pad




OFF Button:  
Sends an OFF Command to the lights linked with this button

Button Operation:  
Press = ON/OFF  
Hold = DIM UP/DOWN

LED Indicator on button press:  
1 Flash = Normal operation  
2 Flashes = Battery Low



[www.qwikswitch.co.za](http://www.qwikswitch.co.za)

## BATTERY REPLACEMENT



Pull Battery out from the top

Insert Battery from the side



**1**

**2**

**3**

LED will flash 3 times to indicate successful power-up.



# Qwik-Switch Scene TX(5 Scene, 1 Off) Installation

## Button Linking:

**1** Connect the receiver to the lights

**2** Hold the LINK button until the LED starts flashing

**3** Then press the Scene button within 25 sec

A Receiver can link up to 30 different buttons.  
 To unlink a button: Repeat steps 2&3.  
 To clear all links in a Receiver:  
 Hold the Receiver Link Button until the LED is ON solid (10 sec) then release.

## Scene Saving:


**1** Link the OFF button to each light, one at a time. This will switch off all selected lights.

**2** Link the scene button to all the lights in the scene. Link one light at a time.

**3** Set the light levels for the Scene, using a standard transmitter, or the test button on the side of the receiver.

**4** Hold the Scene button for 15 seconds to save...Done

## Scene Pad




OFF Button:  
Sends an OFF Command to the lights linked with this button

Button Operation:  
Press = ON/OFF  
Hold = DIM UP/DOWN

LED Indicator on button press:  
1 Flash = Normal operation  
2 Flashes = Battery Low



[www.qwikswitch.co.za](http://www.qwikswitch.co.za)

## BATTERY REPLACEMENT



Pull Battery out from the top

Insert Battery from the side



**1**

**2**

**3**

LED will flash 3 times to indicate successful power-up.